# ZWZD-1616 Breathable Seat Cushion Sensor Array

**Category:** Flexible Fabric · 256 Taxel Cushion Array · **Active Size:** 400 mm × 400 mm (256 Points)

## 1. Product Overview & Description

Large-format breathable fabric matrix for wheelchair anti-decubitus monitoring, automotive driver fatigue assessment, and office ergonomics.

## 2. Mechanical & Electrical Specifications

| Parameter | Specification Value | Test Condition / Notes |
|---|---|---|
| **Sensing Range** | 50 g to 15 kg per taxel | Hyperbolic inverse resistance response |
| **Active Sensing Area** | 400 mm × 400 mm (256 Points) | Defined piezoresistive printed zone |
| **Outer Dimensions** | 440 mm × 440 mm | Inclusive of tail & borders |
| **Nominal Thickness** | 1.50 mm (Breathable Mesh) | Multi-layer PET / Conductive laminate |
| **Actuation Force** | < 20 g | Continuous contact threshold |
| **Response Time** | < 10 milliseconds | Time to reach 90% steady-state |
| **Repeatability** | ±3% | Same device, fixed actuator profile |
| **Hysteresis** | < 12% | Loading vs. unloading curve offset |
| **Operating Temperature** | -20°C to +60°C | Humidity: 0% – 95% RH non-condensing |
| **Mechanical Lifetime** | > 500,000 Seated cycles | Tested under 1kg load cycling |
| **Electrical Connection** | 32-Pin FPC Connector (16 Rows × 16 Cols) | Standard pinout compatible |

## 3. Signal Conditioning & Circuit Integration Guide

FSR sensors exhibit a hyperbolic decrease in electrical resistance as applied compressive force increases. For optimal measurement accuracy:

**A. Transimpedance Inverting Op-Amp Circuit (Recommended):** Connect the FSR between a negative reference voltage (-Vref) and the inverting input of an operational amplifier with a feedback resistor (Rf). The output voltage is directly proportional to applied conductance (and approximately linear to force): $Vout = Vref \times (Rf / Rsensor)$.

**B. Simple Voltage Divider:** Place the FSR in series with a fixed reference resistor (Rm = 1kΩ to 100kΩ) across Vcc and GND. Measure voltage across Rm: $Vout = Vcc \times [Rm / (Rm + Rsensor)]$.

## 4. Custom Engineering & Ordering Information

FSRTEK provides rapid custom tooling within 120 hours for modified sensor dimensions, high-temperature substrates, tailored force sensitivities (10g to 100kg), and multi-channel DAQ acquisition hardware.

**Technical Sales & Sample Inquiries:** sales@fsrtek.com | **Direct Engineer Hotline:** +86 181 2129 1819

**Global Website:** www.fsrtek.com | **Headquarters:** Jiangning District, Nanjing, Jiangsu, China.

© 2026 FSRTEK Sensor Technology (A FlexKYS Brand). Specifications subject to change without notice. All rights reserved.